




# SCH2 Single Piece Strut Clamp for Cable/Conduit – SCH12B



- One-piece cable/conduit clamp with protective boot
- No screws or bolts to drop
- Requires only a screwdriver or nutdriver for installation
- Fits into open side of strut channel
- FM® Specification Tested (from 1/2" to 4" of EMT Conduit Size)



|                             |                                                                              |
|-----------------------------|------------------------------------------------------------------------------|
| Part Number                 | SCH12B                                                                       |
| Material                    | Steel                                                                        |
| Finish                      | Electrogalvanized                                                            |
| Outer Diameter (OD)         | 0.57" – 0.92"                                                                |
| EMT Conduit Size            | 3/4"                                                                         |
| Rigid Conduit/Pipe Size     | 1/2"                                                                         |
| Static Load (F)             | 200 lb                                                                       |
| Certifications              | cULus<br>DIN 4102-12 abP P-3117/339/14-MPA BS (Germany)<br>E30<br>E60<br>E90 |
| Standard Packaging Quantity | 100 pc                                                                       |
| UPC                         | 78285625512                                                                  |

FM is a registered certification mark of FM Approvals LLC, LTD. UL, UR, cUL, cUR, cULus and cURus are registered certification marks of UL LLC.

## WARNING

nVent products shall be installed and used only as indicated in nVent's product instruction sheets and training materials. Instruction sheets are available at [www.erico.com](http://www.erico.com) and from your nVent customer service representative. Improper installation, misuse, misapplication or other failure to completely follow nVent's instructions and warnings may cause product malfunction, property damage, serious bodily injury and death and/or void your warranty.

© 2019 nVent All rights reserved

nVent, nVent CADDY, nVent ERICO, nVent ERIFLEX and nVent LENTON are owned by nVent or its global affiliates.

All other trademarks are the property of their respective owners. nVent reserves the right to change specifications without prior notice.

